



**Office Data Administration System
Fundamentals
Avaya Communication Server 1000**

Release 7.6
NN43001-552
Issue 06.01
March 2013

Notice

While reasonable efforts have been made to ensure that the information in this document is complete and accurate at the time of printing, Avaya assumes no liability for any errors. Avaya reserves the right to make changes and corrections to the information in this document without the obligation to notify any person or organization of such changes.

Documentation disclaimer

"Documentation" means information published by Avaya in varying mediums which may include product information, operating instructions and performance specifications that Avaya generally makes available to users of its products. Documentation does not include marketing materials. Avaya shall not be responsible for any modifications, additions, or deletions to the original published version of documentation unless such modifications, additions, or deletions were performed by Avaya. End User agrees to indemnify and hold harmless Avaya, Avaya's agents, servants and employees against all claims, lawsuits, demands and judgments arising out of, or in connection with, subsequent modifications, additions or deletions to this documentation, to the extent made by End User.

Link disclaimer

Avaya is not responsible for the contents or reliability of any linked websites referenced within this site or documentation provided by Avaya. Avaya is not responsible for the accuracy of any information, statement or content provided on these sites and does not necessarily endorse the products, services, or information described or offered within them. Avaya does not guarantee that these links will work all the time and has no control over the availability of the linked pages.

Warranty

Avaya provides a limited warranty on its hardware and Software ("Product(s)"). Refer to your sales agreement to establish the terms of the limited warranty. In addition, Avaya's standard warranty language, as well as information regarding support for this Product while under warranty is available to Avaya customers and other parties through the Avaya Support website: <http://support.avaya.com>. Please note that if you acquired the Product(s) from an authorized Avaya reseller outside of the United States and Canada, the warranty is provided to you by said Avaya reseller and not by Avaya. "Software" means computer programs in object code, provided by Avaya or an Avaya Channel Partner, whether as stand-alone products or pre-installed on hardware products, and any upgrades, updates, bug fixes, or modified versions.

Licenses

THE SOFTWARE LICENSE TERMS AVAILABLE ON THE AVAYA WEBSITE, [HTTP://SUPPORT.AVAYA.COM/LICENSEINFO](http://support.avaya.com/licenseinfo) ARE APPLICABLE TO ANYONE WHO DOWNLOADS, USES AND/OR INSTALLS AVAYA SOFTWARE, PURCHASED FROM AVAYA INC., ANY AVAYA AFFILIATE, OR AN AUTHORIZED AVAYA RESELLER (AS APPLICABLE) UNDER A COMMERCIAL AGREEMENT WITH AVAYA OR AN AUTHORIZED AVAYA RESELLER. UNLESS OTHERWISE AGREED TO BY AVAYA IN WRITING, AVAYA DOES NOT EXTEND THIS LICENSE IF THE SOFTWARE WAS OBTAINED FROM ANYONE OTHER THAN AVAYA, AN AVAYA AFFILIATE OR AN AVAYA AUTHORIZED RESELLER; AVAYA RESERVES THE RIGHT TO TAKE LEGAL ACTION AGAINST YOU AND ANYONE ELSE USING OR SELLING THE SOFTWARE WITHOUT A LICENSE. BY INSTALLING, DOWNLOADING OR USING THE SOFTWARE, OR AUTHORIZING OTHERS TO DO SO, YOU, ON BEHALF OF YOURSELF AND THE ENTITY FOR WHOM YOU ARE INSTALLING, DOWNLOADING OR USING THE SOFTWARE (HEREINAFTER REFERRED TO INTERCHANGEABLY AS "YOU" AND "END USER"), AGREE TO THESE TERMS AND CONDITIONS AND CREATE A BINDING CONTRACT BETWEEN YOU AND AVAYA INC. OR THE APPLICABLE AVAYA AFFILIATE ("AVAYA").

Heritage Nortel Software

"Heritage Nortel Software" means the software that was acquired by Avaya as part of its purchase of the Nortel Enterprise Solutions Business in December 2009. The Heritage Nortel Software currently available for license from Avaya is the software contained within the list of Heritage Nortel Products located at <http://support.avaya.com/LicenseInfo> under the link "Heritage Nortel Products". For Heritage Nortel Software, Avaya grants Customer a license to use Heritage Nortel Software provided hereunder solely to the extent of the authorized activation or authorized usage level, solely for the purpose specified in the Documentation, and solely as embedded in, for execution on, or (in the event the applicable Documentation permits installation on non-Avaya equipment) for communication with Avaya equipment. Charges for Heritage Nortel Software may be based on extent of activation or use authorized as specified in an order or invoice.

Copyright

Except where expressly stated otherwise, no use should be made of materials on this site, the Documentation, Software, or hardware provided by Avaya. All content on this site, the documentation and the Product provided by Avaya including the selection, arrangement and design of the content is owned either by Avaya or its licensors and is protected by copyright and other intellectual property laws including the sui generis rights relating to the protection of databases. You may not modify, copy, reproduce, republish, upload, post, transmit or distribute in any way any content, in whole or in part, including any code and software unless expressly authorized by Avaya. Unauthorized reproduction, transmission, dissemination, storage, and or use without the express written consent of Avaya can be a criminal, as well as a civil offense under the applicable law.

Third Party Components

"Third Party Components" mean certain software programs or portions thereof included in the Software that may contain software (including open source software) distributed under third party agreements ("Third Party Components"), which contain terms regarding the rights to use certain portions of the Software ("Third Party Terms"). Information regarding distributed Linux OS source code (for those Products that have distributed Linux OS source code) and identifying the copyright holders of the Third Party Components and the Third Party Terms that apply is available in the Documentation or on Avaya's website at: <http://support.avaya.com/Copyright>. You agree to the Third Party Terms for any such Third Party Components.

Note to Service Provider

The Product may use Third Party Components that have Third Party Terms that do not allow hosting and may need to be independently licensed for such purpose.

Preventing Toll Fraud

"Toll Fraud" is the unauthorized use of your telecommunications system by an unauthorized party (for example, a person who is not a corporate employee, agent, subcontractor, or is not working on your company's behalf). Be aware that there can be a risk of Toll Fraud associated with your system and that, if Toll Fraud occurs, it can result in substantial additional charges for your telecommunications services.

Avaya Toll Fraud intervention

If you suspect that you are being victimized by Toll Fraud and you need technical assistance or support, call Technical Service Center Toll Fraud Intervention Hotline at +1-800-643-2353 for the United States and Canada. For additional support telephone numbers, see the Avaya Support website: <http://support.avaya.com>. Suspected security vulnerabilities with Avaya products should be reported to Avaya by sending mail to: securityalerts@avaya.com.

Trademarks

The trademarks, logos and service marks ("Marks") displayed in this site, the Documentation and Product(s) provided by Avaya are the registered or unregistered Marks of Avaya, its affiliates, or other third

parties. Users are not permitted to use such Marks without prior written consent from Avaya or such third party which may own the Mark. Nothing contained in this site, the Documentation and Product(s) should be construed as granting, by implication, estoppel, or otherwise, any license or right in and to the Marks without the express written permission of Avaya or the applicable third party.

Avaya is a registered trademark of Avaya Inc.

All non-Avaya trademarks are the property of their respective owners, and "Linux" is a registered trademark of Linus Torvalds.

Downloading Documentation

For the most current versions of Documentation, see the Avaya Support website: <http://support.avaya.com>.

Contact Avaya Support

See the Avaya Support website: <http://support.avaya.com> for product notices and articles, or to report a problem with your Avaya product. For a list of support telephone numbers and contact addresses, go to the Avaya Support website: <http://support.avaya.com>, scroll to the bottom of the page, and select Contact Avaya Support.

Contents

Chapter 1: New in this release	7
Features.....	7
Other.....	7
Revision history.....	7
Chapter 2: Introduction	9
Subject.....	9
Note on legacy products and releases.....	9
Applicable systems.....	9
Intended audience.....	9
Conventions.....	10
Terminology.....	10
Related information.....	10
Technical Publications.....	10
Online.....	10
Customer service.....	11
Getting technical documentation.....	11
Getting product training.....	11
Getting help from a distributor or reseller.....	11
Getting technical support from the Avaya Web site.....	11
Chapter 3: Description	13
Contents.....	13
Introduction.....	13
Station line designator.....	14
Service activity date.....	14
Enhancements to non-ODAS overlay programs.....	14
Selectable page control.....	15
ODAS overlay programs.....	15
Features print program (LD 81).....	15
Multiple appearance and hunt chain print (LD 82).....	15
Designator sort print (LD 83).....	16
Designator entry program (LD 84 and LD 85).....	16
Call Party Name Display.....	16
Emergency Services Access.....	16
On-Site Notification.....	16
Chapter 4: ODAS programs	19
Contents.....	19
Features print program (LD 81).....	19
Multiple appearance and hunt chain program (LD 82).....	20
Designator sort print program (LD 83).....	23
Designator entry programs (LD 84 and LD 85).....	25
Chapter 5: Engineering	27
Contents.....	27
Memory requirements.....	27
Index	29

Chapter 1: New in this release

The following sections detail what's new with Office Data Administration System for Avaya Communication Server 1000 (Avaya CS 1000) Release 7.6.

- [Features](#) on page 7
- [Other](#) on page 7

Features

There are no updates to the feature descriptions in this document.

Other

Revision history

March 2013 Standard 06.01. This document is up-issued to support Avaya Communication Server 1000 Release 7.6.

October 2011 Standard 05.03. This document is up-issued to remove legacy feature and hardware content that is no longer applicable to or supported by Communication Server 1000 systems.

November 2010 Standard 05.02. This document is up-issued to support Avaya Communication Server 1000 Release 7.5.

November 2010 Standard 05.01. This document is up-issued to support Avaya Communication Server 1000 Release 7.5.

June 2010 Standard 04.01. This document is up-issued to support Avaya Communication Server 1000 Release 7.0.

May 2009 Standard 03.01. This document is up-issued to support Communication Server 1000 Release 6.0.

December 2007 Standard 02.01. This document is up-issued for Communication Server 1000 Release 5.5.

June 2007 Standard 01.02. This document is up-issued to remove the confidential statement.

May 2007 Standard 01.01. This document is issued to support Communication Server 1000 Release 5.0. This document contains information previously contained in the following legacy document, now retired: *Office Data Administration System: Description and Engineering (553-3001-352)*. No new content has been added for Communication Server 1000 Release 5.0. All references to Communication Server 1000 Release 4.5 are applicable to Communication Server 1000 Release 5.0.

August 2005 Standard 3.00. This document is up-issued to support Communication Server 1000 Release 4.5.

September 2004 Standard 2.00. This document is up-issued for Communication Server 1000 Release 4.0.

October 2003 Standard 1.00. This document is new for Succession 3.0. It was created to support a restructuring of the Documentation Library. This document contains information previously contained in the following legacy document, now retired: *Office Data Administration System: Description and Engineering (553-2721-100)*.

Chapter 2: Introduction

This document is a global document. Contact your system supplier or your Avaya representative to verify that the hardware and software described are supported in your area.

Subject

This document describes the features, programs, and engineering requirements of Office Data Administration System (ODAS). ODAS enables record keeping for telephones and attendant consoles.

Note on legacy products and releases

This document contains information about systems, components, and features that are compatible with Avaya Communication Server 1000 (Avaya CS 1000) software. For more information on legacy products and releases, click the **Documentation** link under **Support** on the Avaya home page:

<http://www.avaya.com>

Applicable systems

This document applies to the following systems:

- Avaya Communication Server 1000E (Avaya CS 1000E)
- Avaya Communication Server 1000M Single Group (Avaya CS 1000M SG)
- Avaya Communication Server 1000M Multi Group (Avaya CS 1000M MG)

Intended audience

This document is intended for individuals responsible for configuring the Office Data Administration System.

Conventions

Terminology

In this document, the following systems are referred to generically as "system":

- Avaya Communication Server 1000M (Avaya CS 1000M)
- Avaya Communication Server 1000E (Avaya CS 1000E)
- Meridian 1

The following systems are referred to generically as "Large System":

- Communication Server 1000M Single Group (CS 1000M SG)
- Communication Server 1000M Multi Group (CS 1000M MG)
- Meridian 1 PBX 61C, CP IV
- Meridian 1 PBX 81C, CP IV

Related information

This section lists information sources that relate to this document.

Technical Publications

The following Technical Publications are referenced in this document:

- *Avaya Software Input Output Administration (NN43001-611)*
- *Avaya Communication Server 1000M and Meridian 1 Large System Planning and Engineering (NN43021-220)*

Online

To access Avaya documentation online, click the **Documentation** link under **Support** on the Avaya home page:

<http://www.avaya.com>

Customer service

Visit the Avaya Web site to access the complete range of services and support that Avaya provides. Go to <http://www.avaya.com> or go to one of the pages listed in the following sections.

- [Getting technical documentation](#) on page 11
- [Getting product training](#) on page 11
- [Getting help from a distributor or reseller](#) on page 11
- [Getting technical support from the Avaya Web site](#) on page 11

Getting technical documentation

To download and print selected technical publications and release notes directly from the Internet, go to www.avaya.com/support.

Getting product training

Ongoing product training is available. For more information or to register, you can access the Web site at www.avaya.com/support. From this Web site, you can locate the Training contacts link on the left-hand navigation pane.

Getting help from a distributor or reseller

If you purchased a service contract for your Avaya product from a distributor or authorized reseller, contact the technical support staff for that distributor or reseller for assistance.

Getting technical support from the Avaya Web site

The easiest and most effective way to get technical support for Avaya products is from the Avaya Technical Support Web site at www.avaya.com/support.

Chapter 3: Description

Contents

This section contains information on the following topics:

- [Introduction](#) on page 13
- [Station line designator](#) on page 14
- [Service activity date](#) on page 14
 - [Enhancements to non-ODAS overlay programs](#) on page 14
- [Selectable page control](#) on page 15
- [ODAS overlay programs](#) on page 15
 - [Features print program \(LD 81\)](#) on page 15
 - [Multiple appearance and hunt chain print \(LD 82\)](#) on page 15
 - [Designator sort print \(LD 83\)](#) on page 16
 - [Designator entry program \(LD 84 and LD 85\)](#) on page 16
- [Call Party Name Display](#) on page 16
- [Emergency Services Access](#) on page 16
 - [On-Site Notification](#) on page 16

Introduction

Office Data Administration System (ODAS) is an optional software package. This feature assists in keeping records of information regarding telephones and attendant consoles.

ODAS allows you to perform the following functions:

- assign a one-to-six-character alphanumeric station line designator (DES).
- insert the date of all service change activity on the Terminal Number (TN)

- print individual items on individual pages, including system and customer numbers, and a title for each page
- list or count all stations by telephone type, feature type, or both
- list Multiple Appearance Directory Numbers (MADN)
- list hunting patterns for individual Directory Numbers (DN)
- list telephones in alphanumerical order according to DESs
- enter or change DESs at an accelerated rate

The following sections describe these features in more detail.

Station line designator

The station line designator (DES) is a one-to-six-character alphanumeric code assigned to individual telephones through overlay programs.

You can use the DES to do the following:

- identify telephones according to a system of numbering and naming that is meaningful to you
- get telephone data block printouts without the need to enter the TN or the DN

You must respond to the DES field when you use LDs 10 and 11 to install telephones. You must respond to the DES field in LD 27 when you install a Digital Subscriber Loop (DSL) data block.

Service activity date

The service activity (ACT) date indicates the last date a service change was performed on a particular TN. The system automatically enters and updates the ACT date whenever a service change is made. When requested, the system updates the ACT date of all TNs to the present system date. You can use ODAS print programs to print information according to a particular ACT date.

Enhancements to non-ODAS overlay programs

The ACT date is automatically updated to the present system date for analog (500/2500-type) telephones (LD 10), Meridian 1 proprietary telephones (LD 11), attendant consoles (LD 12), Digitone receivers (LD 13), and trunk data blocks (LD 14) whenever a service change is made to the individual TN. It is also updated whenever the ACT date is reset to the present system date through a print program. LD 20 includes prompts for station DES, ACT DATE, and PAGE

control. LD 22 includes prompts for ACT date, PAGE control, and reset ACT date. LD 10 and LD 11 include the insertion of a station DES. See *Avaya Software Input Output Administration (NN43001-611)* for complete information.

Selectable page control

Selectable page control permits individual printouts for each page on standard 11-in. (280-mm) fanfold paper. Each page contains information about the individual item. The printout includes the system and customer numbers as well as the printout title. The customer number appears when requested at the CUST prompt.

ODAS overlay programs

Features print program (LD 81)

The features print program provides a list or count of the number of telephones in your system. The system may be prompted to supply the information based on one or more of the following:

- telephone type
- feature type
- telephone and feature type
- a single customer or a range of customers
- a predetermined ACT date
- DES

This program also includes selectable page control and ACT date resetting capabilities.

Multiple appearance and hunt chain print (LD 82)

The multiple appearance and hunt chain print program provides a printout of stations with multiple appearance DNs, single appearance DNs appearing on telephones with multiple appearance DNs, and hunting patterns. The system can be prompted to supply the information based on one or more of the following:

- a single DN or a range of DNs
- a single customer or a range of customers

Description

- a predetermined ACT date
- DES

This program also includes selectable page control and ACT date resetting capabilities.

Designator sort print (LD 83)

The designator sort print program produces a printout of TNs in DES order. The system can be prompted to supply the information based on the following:

- single line listing of TNs in DES order or a detailed TN print in DES order
- a single customer or a range of customers

This program also includes selectable page control and ACT date resetting capabilities.

Designator entry program (LD 84 and LD 85)

The designator entry program permits entering or changing a DES on analog (500/2500-type) telephones (LD 84) and Meridian 1 proprietary telephones (LD 85) at an accelerated rate. These programs perform an easy change similar to those in LDs 10 and 11. See *Avaya Software Input Output Administration (NN43001-611)* for complete information.

Call Party Name Display

In LD 95, you can activate the display of the DES for MADNs. For display purposes, the DES characters are appended to the Call Party Name Display (CPND) name. Initial CPND name characters can be chopped off in favor of DES characters at the end, when the display cannot accommodate all characters.

Emergency Services Access

On-Site Notification

When an emergency call is initiated by a telephone user, the ODAS designator associated with the originating telephone is included as part of the On-Site Notification (OSN) call record sent

to the OSN output or maintenance device. The DES is also part of the information shown on the OSN telephone display.

Description

Chapter 4: ODAS programs

Contents

This section contains information on the following topics:

[Features print program \(LD 81\)](#) on page 19

[Multiple appearance and hunt chain program \(LD 82\)](#) on page 20

[Designator sort print program \(LD 83\)](#) on page 23

[Designator entry programs \(LD 84 and LD 85\)](#) on page 25

Features print program (LD 81)

Prompts and responses for LD 81 appear below.

Table 1: LD 81: List or count telephones.

Prompt	Response	Description
REQ	LST CNT	List or count stations with features.
CUST	xx	Customer number as defined in LD 15.
DATE	ACT dd mmm yyyy <cr>	TN service changes on or after the ACT date. Print from selected date. Ignore service change date.
PAGE	YES <cr>	Page control. No page control.
DES	d...d d+ + <cr>	Print all telephones with this DES. (Up to 6 alphanumeric characters.) Print all telephones with DES starting with d. Print all telephones with no DES assigned. Print data for all telephones.
FEAT	ALL xxxx	Prints all features. Print the specified feature, see <i>Avaya Software Input Output Administration (NN43001-611)</i> .

Prompt	Response	Description
NACT	<cr>	When DATE or DES is answered (above), carriage return means the system searches only for the DATE and/or DES input. If a feature was entered, <cr> means no more features to be entered.
	YES	Resets ACT date to present system date.
	<cr> END	Return to REQ, does not reset date. Exit program. NACT appears after printout is completed.

[Table 2: Typical printout of a list of telephones with the Speed Call Controller \(SCC\) feature \(LD 81\)](#) on page 20 and [Table 3: Typical printout of a count of telephones sorted by feature type \(LD 81\)](#) on page 20 list typical printout formats for LD 81.

Table 2: Typical printout of a list of telephones with the Speed Call Controller (SCC) feature (LD 81)

Feat	Cust	DN	LSN O	TN	Type	Key	DES	Act date
SCC	00	2000	0000	TN 00 0 01 0	500		ABCD A	1 JAN1979
SCC	00	2001	0001	TN 00 0 01 1	500		ABCD B	1 JAN1979
SCC	00	2002	0000	TN 00 0 01 2	500		DEEE	10 APR1979
SCC	00	2003	0000	TN 00 0 01 3	2500		ABCD D	10 APR1979
SCC	00	3000	0002	TN 00 0 04 0	2616	4	HIB	10 APR1979

Table 3: Typical printout of a count of telephones sorted by feature type (LD 81)

Feature	Customer	Count	Total	2616	500	2006
ADL	00	CNT	1	1	0	0
AD3	00	CNT	1	1	0	0
AO6	00	CNT	2	2	0	3
ARC	00	CNT	2	2	1	0
PUA	ALL	CNT	3	2	1	0
PUD	ALL	CNT	0	0	0	0

Multiple appearance and hunt chain program (LD 82)

Prompts and responses for LD 82 appear below.

Table 4: LD 82: Prompts and responses.

Prompt	Response	Description
REQ	MAP	Multiple Appearance. Print Multiple Appearance DN (MADN) and associated TNs. The hunt pattern displayed shows only the first TN in an MADN hunt group.
	MAG	Multiple Appearance Groups. Print Multiple Appearance Groups, including all single appearance DN assigned on telephones that have Multiple Call assignments.
	HNT	Hunt pattern, single step in either direction. Short hunting is not shown.
CUST	xx	Customer number as defined in LD 15.
DATE	ACT dd mmm yyyy <cr>	TN service changes on or after the ACT date. Print from selected date. Ignore service change date.
PAGE	YES <cr>	Page control. No page control.
DES	d...d	Print all telephones with this DES. (Up to 6 alphanumeric characters.)
	d+ + <cr>	Print all telephones with DES starting with d. Print all telephones with no DES assigned. Print data for all telephones.
DN	x...x ALL <cr>	Single DN or a range of DNs (0–9999999). Print all MAG or MAP DNs. All DNs.
NACT	YES <cr> END	Resets ACT date to present system date. Return to REQ, does not reset date. Exit program. NACT appears after printout is completed.

Typical printout formats for LD 82 appear in [Table 5: Typical MAP printout \(LD 82\)](#) on page 21, [Table 6: Typical Multiple Appearance Group \(MAG\) printout \(LD 82\)](#) on page 22, and [Table 7: Typical hunt chain print \(LD 82\)](#) on page 23.

Table 5: Typical MAP printout (LD 82)

MAG ¹	Cust ²	DN ³	TN	Note ³	Type	Key	DES	Act date
001	00	200	00 1 01 2	***01	2616	03	YJK	10 JUN 1979
			00 1 01 3	HNT205	2616	08	YM N	2 APR 1979

MAG ¹	Cust ²	DN ³	TN	Note ³	Type	Key	DES	Act date
		201	00 0 01 0	HNT NONE	2616	03	AZK	1 MAY 1979
			00 1 01 2	***01	2616	02	YJK	10 JUN 1979
		204	00 0 01 0	HNT NONE	2616	03	AZK	1 MAY 1979
			00 1 02 3	***01	500		AM M	2 JAN 1979
		203	00 1 01 2	HNT NONE	2616	04	YJK	10 JAN 1979
			00 0 02 2	***01	500		AM K	10 SEP 1979

Note:
The Multiple Appearance Group (MAG) number is determined by the system. It assigns the group numbers in ascending order.

Note:
The DN is indicated only on the lowest TN of the multiple appearance group. Single appearance DNs have only one TN listed.

Note:
The system uses the first TN of the multiple appearance group to determine hunting. ***01 indicates the order the TN is stored in the system (1–15). The first TN in the list (0) is identified either by a HNT number or HNT NONE.

Table 6: Typical Multiple Appearance Group (MAG) printout (LD 82)

MAG ¹	Cust ²	DN ³	TN	Note ³	Type	Key	DES	Act date
001	00	300	00 0 04 0	HNT 330	2616	00	BV M	2 JAN 1980
			302 00 0 04 0	HNT 330	2616	01	BV M	2 JAN 1980
			00 0 04 1	***01	2616	01	BFO	3 FEB 1980
		302	00 0 04 0	***01	2616	02	BV M	2 JAN 1980
			00 0 04 1	HNT 330	2616	02	BFO	3 FEB 1980
		303	00 0 04 0	HNT 330	500	03	BV M	2 JAN 1980
			00 0 04 1	***01	2616	03	BFO	3 FEB 1980
		304	00 0 04 0	HNT 330	2616	04	BV M	2 JAN 1980
		307	00 0 04 0	HNT 330	2616	05	BV M	2 JAN 1980

MAG ¹	Cust ²	DN ³	TN	Note ³	Type	Key	DES	Act date
		310	00 0 04 1		2616	00	BFO	3 FEB 1980
		400	00 0 04 0	HNT NONE	2616	06	BV M	2 JAN 1980
002	00	200	24 0 01 0	***01	500		GBA	9 MAR 1980
		200	24 0 01 3	HNT 309	2500		JLO	8 MAR 1980

Note:
The Multiple Appearance Group (MAG) number is determined by the system and assigns the group numbers in ascending order.

Note:
The DN is indicated only on the lowest TN of multiple appearance. Single appearance DN have only one TN listed.

Note:
The system uses the first TN of the multiple appearance to determine hunting. ***01 indicates the order the TN is stored in the system (1–15). The first TN in the list (0) is identified either by a HNT number or HNT NONE.

Table 7: Typical hunt chain print (LD 82)

Cust	DN	Hunt	DN	TN	Telephone type	Key	DES	ACT date
00	5040		5040	016 0 09 00	3000	00	ABC	30 OCT 1991
		FROM	2032	049 0 09 00	2500		YJK	31 OCT 1991
00	2032	TO	5040	016 0 09 00	3000	00	ABC	30 OCT 1991
			2032	049 0 09 00	2500		YJK	31 OCT 1991

Note:
** indicates a multiple appearance DN.

Designator sort print program (LD 83)

Prompts and responses for LD 83 appear below.

Table 8: LD 83: Prompts and responses.

Prompt	Response	Description
REQ	LST TNB	Single line of information for each TN in DES order. TNB printouts in DES order.
CUST	xx	Customer number as defined in LD 15.
PAGE	YES <cr>	Page control. No page control.
NACT	YES <cr> END	Resets ACT date to present system date. Return to REQ, does not reset date. Exit program. NACT appears after printout is completed.

Typical printout formats for LD 83 appear in [Table 9: Typical list printout format \(LD 83\)](#) on page 24 and [Table 10: Typical TN printout format \(LD 83\)](#) on page 24.

Table 9: Typical list printout format (LD 83)

DES	ACT	Cust TN	Type	Density	Prime DN
ABC	24 OCT 1979	00 00 4 02 3	2616	DD	3001
ABD	10 NOV 1979	00 00 4 03 0	500	SD	

Table 10: Typical TN printout format (LD 83)

DES	AIB
TN	00 0 02 1
TYPE	2616
CDEN	DD
CUST	0
KLS	1
FDN	2564
TGAR	0
RNPG	0
IAPG	0
CLS	UNR FBD WTA LPR MTD FNA HTD
HUNT	000
KEY	00 SCR 250 01 02 03 04 05 06 07 08 09 RLS
DATE	2 JUL 1980

Designator entry programs (LD 84 and LD 85)

LD 84 allows the addition of line designators to existing analog (500/2500-type) telephones.

LD 85 allows the addition of line designators to existing Meridian 1 proprietary telephones.

If the telephone is active on a call, the station is disconnected after the last <cr>.

Prompts and responses for LD 84 and LD 85 appear below.

Table 11: LD 84/LD 85: Prompts and responses.

Prompt	Response	Description
TN	l s c u	Terminal Number. Format for Large System and Avaya Communication Server 1000E system, where l = loop, s = shelf, c = card, u = unit.
	END	Exit the program.
DES	x...x	Designator. (Up to 6 alphanumeric characters.)

Chapter 5: Engineering

Contents

This section contains information on the following topics:

[Memory requirements](#) on page 27

Memory requirements

In addition to the data-store requirements given in *Avaya Communication Server 1000M and Meridian 1 Large System Planning and Engineering (NN43021-220)*, the ODAS feature requires the extra storage indicated in [Table 12: ODAS memory requirements](#) on page 27.

Table 12: ODAS memory requirements

Type of store	Requirements (words)
Program store	1100
Protected data-store activity date per TN in system	1
Station line DES per telephone	2

Index

A

ACT (service activity) date [14](#), [15](#)
 described [14](#)
 resetting [14](#), [15](#)
 updating [14](#)

C

customer numbers [15](#)

D

designator entry program (LD84/85) [16](#), [25](#)
designator sort print program (LD83) [16](#), [23](#)

E

engineering data [27](#)

F

features print program (LD81) [15](#), [19](#)

H

hunt chain printouts [20](#)

L

list printouts [23](#)

M

MAG (Multiple Appearance Group) [20](#)

memory requirements [27](#)
multiple appearance and hunt chain program (LD82)
 [15](#), [20](#)
Multiple Appearance Group (MAG) [20](#)

O

ODAS (Office Data Administration System) [13](#), [14](#), [19](#), [27](#)
 described [13](#)
 engineering data [27](#)
 enhancements to other programs [14](#)
 programs [19](#)

P

printing [15](#), [16](#)
 customer numbers [15](#)
 telephone lists/counts [15](#)
 TNs in DES order [16](#)
printouts [14](#), [15](#), [19](#), [20](#), [23](#)
 designator sort print program (LD83) [23](#)
 hunt chain (LD82) [20](#)
 LD81 formats [19](#)
 list [23](#)
 MAG (LD82) [20](#)
 MAP (LD82) [20](#)
 selectable page control [15](#)
 telephone data block [14](#)
 TN [23](#)

R

resetting ACT date [14](#), [15](#)

S

selectable page control [15](#)
station line designator (DES) [14](#), [16](#)

T

telephone data block printouts [14](#)
Terminal Number (TN) [14](#), [23](#)

